

Recent Additions

CD54AC109/3A CD54ACT109/3A

SWITCHING CHARACTERISTICS: AC Series; $t_i, t_r = 3 \text{ ns}$, $C_L = 50 \text{ pF}$ (Worst Case)

CHARACTERISTICS	SYMBOL	V_{cc} (V)	-55 to +125°C		UNITS
			MIN.	MAX.	
Propagation Delays: CP (\bar{CP}) to Q, \bar{Q}	t_{PLH} t_{PHL}	1.5 3.3* 5†	— 2.7 1.7	129 14.4 10.3*	ns
\bar{S}, \bar{R} to Q, \bar{Q}	t_{PLH} t_{PHL}	1.5 3.3 5	— 3.2 2.1	153 17.1 12.2*	ns
Power Dissipation Capacitance	$C_{PD\$}$	—	—	—	pF
Input Capacitance	C_I	—	—	10	pF

SWITCHING CHARACTERISTICS: ACT Series; $t_i, t_r = 3 \text{ ns}$, $C_L = 50 \text{ pF}$ (Worst Case)

CHARACTERISTICS	SYMBOL	V_{cc} (V)	-55 to +125°C		UNITS
			MIN.	MAX.	
Propagation Delays: CP (\bar{CP}) to Q, \bar{Q}	t_{PLH}	5†	1.7	10.3*	ns
\bar{S}, \bar{R} , to Q, \bar{Q}	t_{PHL}	5	2.3	13.5*	ns
Power Dissipation Capacitance	$C_{PD\$}$	—	—	—	pF
Input Capacitance	C_I	—	—	10	pF

*3.3 V: min. is @ 3.6 V
max. is @ 3 V

§ C_{PD} is used to determine the dynamic power consumption per flip-flop.

For AC, $P_D = C_{PD}V_{cc}^2 f_i + \sum (C_L V_{cc}^2 f_o)$

For ACT, $P_D = C_{PD}V_{cc}^2 f_i + \sum (C_L V_{cc}^2 f_o) + V_{cc} \Delta I_{cc}$ where f_i = input frequency
 f_o = output frequency
 C_L = output load capacitance
 V_{cc} = supply voltage

†5 V: min. is @ 5.5 V
max. is @ 4.5 V

(Limits with black dots (•) are tested 100%).

CD54AC112/3A CD54ACT112/3A

Dual “J-K” Flip-Flop with Set and Reset


Negative-Edge-Triggered (J, K)

The RCA CD54AC112 and CD54ACT112 are dual “J-K” flip-flops with set and reset that utilize the new RCA ADVANCED CMOS LOGIC technology. These flip-flops have independent J, K, Set, Reset, and Clock inputs and Q and \bar{Q} outputs. The CD54AC/ACT112 changes state on the negative-going transition of the clock pulse. Set and Reset are accomplished asynchronously by low-level inputs.

The CD54AC112 and CD54ACT112 are supplied in 16-lead dual-in-line ceramic packages (F suffix).

Package Specifications

(See Section 11, Fig. 11)



FUNCTIONAL DIAGRAM

Recent Additions**CD54AC112/3A****CD54ACT112/3A****Static Electrical Characteristics** (Limits with black dots (•) are tested 100%).

CHARACTERISTICS	TEST CONDITIONS		V _{CC} (V)	AMBIENT TEMPERATURE (T _A) - °C				UNITS
				+25		-55 to +125		
	MIN.	MAX.		MIN.	MAX.	MIN.	MAX.	
Quiescent Supply Current (FF) I _{CC}	V _{CC} or GND	0	5.5	—	4•	—	80•	μA

The complete static electrical test specification consists of the above by-type static tests combined with the standard static tests in the beginning of this section.

ACT INPUT LOADING TABLE

INPUT	UNIT LOAD*
J, CP, \bar{CP}	1
K	0.53
\bar{S}, \bar{R}	0.58

*Unit load is ΔI_{CC} limit specified in Static Characteristics Chart, e.g., 2.4 mA max. @ 25°C.

Burn-In Test-Circuit Connections

Identical to CD54HC/HCT112/3A, page 5-44.

SWITCHING CHARACTERISTICS: AC Series; t_r, t_f = 3 ns, C_L = 50 pF (Worst Case)

CHARACTERISTICS	SYMBOL	V _{CC} (V)	-55 to +125°C		UNITS
			MIN.	MAX.	
Propagation Delays: CP (\bar{CP}) to Q, \bar{Q}	t _{PLH} t _{PHL}	1.5 3.3* 5†	— 4.3 3.1	129 14.4 10.3*	ns
\bar{S}, \bar{R} to Q, \bar{Q}	t _{PLH} t _{PHL}	1.5 3.3 5	— 5.1 3.7	153 17.1 12.2*	ns
Power Dissipation Capacitance	C _{PD\$}	—	56 Typ.		pF
Input Capacitance	C _I	—	—	10	pF

SWITCHING CHARACTERISTICS: ACT Series; t_r, t_f = 3 ns, C_L = 50 pF (Worst Case)

CHARACTERISTICS	SYMBOL	V _{CC} (V)	-55 to +125°C		UNITS
			MIN.	MAX.	
Propagation Delays: CP (\bar{CP}) to Q, \bar{Q}	t _{PLH}	5†	3.1	10.3*	ns
\bar{S}, \bar{R} , to Q, \bar{Q}	t _{PHL}	5	3.7	12.2*	ns
Power Dissipation Capacitance	C _{PD\$}	—	56 Typ.		pF
Input Capacitance	C _I	—	—	10	pF

*3.3 V: min. is @ 3.6 V
max. is @ 3 V

§C_{PD} is used to determine the dynamic power consumption per flip-flop.

For AC, P_D = C_{PD}V_{CC}²f_i + Σ (C_LV_{CC}²f_o)

†5 V: min. is @ 5.5 V
max. is @ 4.5 V

For ACT, P_D = C_{PD}V_{CC}²f_i + Σ (C_LV_{CC}²f_o) + V_{CC}ΔI_{CC} where f_i = input frequency
f_o = output frequency
C_L = output load capacitance
V_{CC} = supply voltage

(Limits with black dots (•) are tested 100%).